TESTING IQM: A SYSTEM FOR REAL-TIME MONITORING OF COMPLEX RADIOTHERAPY TREATMENTS




Talamonti C*°, Marrazzo L°, Calusi S*, Arilli C°, Casati M, Compagnucci A, Bonomo P^, Livi L*^, Pallotta S*°



*University of Florence-Department of Experimental and Clinical Biomedical Sciences "Mario Serio", Florence, Italy;
°AOU Careggi- Physic Unit Florence, Italy; Florence, Italy; ^AOU Careggi-Radiotherapy Unit Florence, Italy.

AIM: To test the **Integral Quality Monitoring** (IQM) device (iRT Systems GmbH, Koblenz, Germany): a system for online monitoring of Intensity Modulated Radiation Therapy (IMRT) treatments.






IMRT online monitoring



IQM = It is a large area ionization chamber [1], with a gradient in the electrode plate separation, and a calculation algorithm to predict the signal based on the field information received from the treatment planning system.


The signal from the ionization chamber provides a spatially dependent (one-dimensional) dose-area-product signal for each beam segment.








TESTS


INTRA-FRACTION Repeatability was checked by delivering 15 times (about 2 hours) the same plan composed by 17 square fields 4cm x4cm and 1 larger field 10cmx10cm irradiating different regions of the detector.













INTER-FRACTION Detector Repeatability Inter-fraction detector repeatability was checked by delivering three IMRT treatments for more than seventy times in a period of thirty days. The chosen treatments were: a Head & Neck (H&N), a Prostate and a test IMRT treatment. For each segment of the IMRT treatment σ and M were evaluated over the number of repetitions (21 for H&N; 30 for prostate and test IMRT). In H&N and prostate tests gantry rotation and small field of different shape and size were considered.



treatment composed by seven beams (gantry angles = 0°, 40°, 80°, 140°, 220°, 280°, 320°) generating five new treatments. Errors were induced modifying the number of delivered MU (between 1 and 3) and by introducing small deviations in leaf positions for each segment of each beam (mimicking an MLC bank error).

Much larger errors were found for field of small size (approx. 6cm²). Global and local intra and inter-fraction detector repeatability results, shown in the the table below, demonstrate the optimal detector performances.

Repeata bility	Intra-fraction σ/M [%] <i>Test IMRT</i>	Inter-fraction σ/M [%]		
		Head & Neck	Prostate	Test IMRT
Global	0.08	0.72	0.67	0.96
Local (mean+σ)	0.15±0.09	0.36±0.36	0.28±0.54	0.15±0.17



correspondent beam with induced errors in MUs.

al acquired

Counts registered w

170000

150000
150000
140000
130000
100000
0
2
4
6
8
beam

Registered counts with 1 mm induced error on leaf positions

Percentage differences between the IQM signal acquired
for each beam of the reference treatment and f the leaf positions of bank n°1 and for banks 1&2

Conclusions: IQM provides optimal performance for signal reproducibility of complex IMRT plans. It is also capable of detecting small errors in MU and leaves position sufficient for clinical practice.